

10 LAYERS january 2004



10 LAYERS 1,55 +/-0,15 LAB CODE: 26

MATERIAL	THICKNESS
Basic copper	0,017
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,178	0,18 +/-0,03
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,178	0,18 +/-0,03
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,178	0,18 +/-0,03
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,178	0,18 +/-0,03
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,017

10 LAYERS 1,90 +/- 0,2 LAB CODE: 302

MATERIAL	THICKNESS
Basic copper	0,017
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,254	0,24 +/-0,03
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,254	0,24 +/-0,03
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,254	0,24 +/-0,03
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,254	0,24 +/-0,03
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,017

10 LAYERS 2,0 +/- 0,2 LAB CODE: 310

MATERIAL	THICKNESS
Basic copper	0,017
Prepreg 2113(2)	0,176 +/-0,02
Basic copper	0,035
FR4 0,178	0,18 +/-0,03
Basic copper	0,035
Prepreg 2113(2)	0,176 +/-0,03
Basic copper	0,035
FR4 0,178	0,18 +/-0,03
Basic copper	0,035
Prepreg 2113(2)	0,176 +/-0,03
Basic copper	0,035
FR4 0,178	0,18 +/-0,03
Basic copper	0,035
Prepreg 2113(2)	0,176 +/-0,03
Basic copper	0,035
FR4 0,178	0,18 +/-0,03
Basic copper	0,035
Prepreg 2113(2)	0,176 +/-0,02
Basic copper	0,017

10 LAYERS 2,30 +/-0,2 LAB CODE: 152

MATERIAL	THICKNESS
Basic copper	0,017
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,356	0,35 +/-0,04
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,356	0,35 +/-0,04
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,356	0,35 +/-0,04
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,356	0,35 +/-0,04
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,017

10 LAYERS 3,10 +/- 0,3 LAB CODE: 225

MATERIAL	THICKNESS
Basic copper	0,017
Prepreg 2113(2)	0,176 +/-0,02
Basic copper	0,035
FR4 0,35	0,35 +/-0,04
Basic copper	0,035
Prepreg 7628(2)	0,346 +/-0,03
Basic copper	0,035
FR4 0,35	0,35 +/-0,04
Basic copper	0,035
Prepreg 7628(2)	0,346 +/-0,03
Basic copper	0,035
FR4 0,35	0,35 +/-0,04
Basic copper	0,035
Prepreg 7628(2)	0,346 +/-0,03
Basic copper	0,035
FR4 0,35	0,35 +/-0,04
Basic copper	0,035
Prepreg 2113(2)	0,176 +/-0,02
Basic copper	0,017