

6 LAYERS january 2004



6 LAYERS 0,9 +/- 0,10 LAB CODE: 160

MATERIAL	THICKNESS
Basic copper	0,017
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,178	0,18 +/-0,03
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,178	0,18 +/-0,03
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035

6 LAYERS 1,0 +/- 0,1 LAB CODE: 161

MATERIAL	THICKNESS
Basic copper	0,017
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,254	0,24 +/-0,03
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,254	0,24 +/-0,03
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,017

6 LAYERS 1,2 +/-0,1 LAB CODE:195

MATERIAL	THICKNESS
Basic copper	0,017
Prepreg 2113(2)	0,176 +/-0,02
Basic copper	0,035
FR4 0,254	0,24 +/-0,03
Basic copper	0,035
Prepreg 2113(2)	0,176 +/-0,02
Basic copper	0,035
FR4 0,254	0,24 +/-0,03
Basic copper	0,035
Prepreg 2113(2)	0,176 +/-0,02
Basic copper	0,017

6 LAYERS 1,55 +/-0,15 LAB CODE:172

MATERIAL	THICKNESS
Basic copper	0,017
Prepreg 2113(2)	0,176 +/-0,02
Basic copper	0,035
FR4 0,356	0,35 +/-0,04
Basic copper	0,035
Prepreg 7628(2)	0,346 +/-0,03
Basic copper	0,035
FR4 0,356	0,35 +/-0,04
Basic copper	0,035
Prepreg 2113(2)	0,176 +/-0,02
Basic copper	0,017

6 LAYERS 1,75 +/-0,15 LAB CODE:196

MATERIAL	THICKNESS
Basic copper	0,017
Prepreg 7628(2)	0,346 +/-0,03
Basic copper	0,035
FR4 0,356	0,35 +/-0,04
Basic copper	0,035
Prepreg 2113(2)	0,176 +/-0,03
Basic copper	0,035
FR4 0,356	0,35 +/-0,04
Basic copper	0,035
Prepreg 7628(2)	0,346 +/-0,03
Basic copper	0,017

6 LAYERS 1,95 +/-0,20 LAB CODE:296

MATERIAL	THICKNESS
Basic copper	0,017
Prepreg 7628(2)	0,346 +/-0,03
Basic copper	0,035
FR4 0,508	0,51 +/-0,05
Basic copper	0,035
Prepreg 2113(2)	0,176 +/-0,02
Basic copper	0,035
FR4 0,508	0,51 +/-0,05
Basic copper	0,035
Prepreg 7628(2)	0,346 +/-0,03
Basic copper	0,017

6 LAYERS 2,3 +/-0,2 LAB CODE:203

MATERIAL	THICKNESS
Basic Copper	0,017
Prepreg 2113(2)	0,176 +/-0,02
Basic Copper	0,035
FR4 0,737	0,73 +/-0,06
Basic Copper	0,035
Prepreg 7628(2)	0,346 +/-0,03
Basic Copper	0,035
FR4 0,737	0,73 +/-0,06
Basic Copper	0,035
Prepreg 2113(2)	0,176 +/-0,02
Basic Copper	0,017

6 LAYERS 3,2 +/-0,3 LAB CODE:61

MATERIAL	THICKNESS
Basic Copper	0,017
Prepreg 7628(3)	0,519 +/-0,05
Basic Copper	0,035
FR4 0,737	0,73 +/-0,06
Basic Copper	0,035
Prepreg 7628(3)	0,519 +/-0,05
Basic Copper	0,035
FR4 0,737	0,73 +/-0,06
Basic Copper	0,035
Prepreg 7628(3)	0,519 +/-0,05
Basic Copper	0,017