

# 8 LAYERS january 2004



## 8 LAYERS 1,1 +/-0,1 LAB CODE: 299

MATERIAL	THICKNESS
Basic copper	0,017
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,127	0,13 +/-0,02
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,127	0,13 +/-0,02
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,127	0,13 +/-0,02
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,017

## 8 LAYERS 1,6 +/-0,15 LAB CODE: 217

MATERIAL	THICKNESS
Basic copper	0,017
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,035
FR4 0,254	0,24 +/-0,03
Basic copper	0,035
Prepreg 2113(2)	0,176 +/-0,02
Basic copper	0,035
FR4 0,254	0,24 +/-0,03
Basic copper	0,035
Prepreg 2113(2)	0,176 +/-0,02
Basic copper	0,035
FR4 0,254	0,24 +/-0,03
Basic copper	0,035
Prepreg 1080(2)	0,13 +/-0,01
Basic copper	0,017

## 8 LAYERS 2,0 +/-0,2 LAB CODE: 210

MATERIAL	THICKNESS
Basic copper	0,017
Prepreg 2113(2)	0,176 +/-0,02
Basic copper	0,035
FR4 0,356	0,35 +/-0,04
Basic copper	0,035
Prepreg 2113(2)	0,176 +/-0,02
Basic copper	0,035
FR4 0,356	0,35 +/-0,04
Basic copper	0,035
Prepreg 2113(2)	0,176 +/-0,02
Basic copper	0,035
FR4 0,356	0,35 +/-0,04
Basic copper	0,035
Prepreg 2113(2)	0,176 +/-0,02
Basic copper	0,017

## 8 LAYERS 2,30 +/-0,2 LAB CODE: 211

MATERIAL	THICKNESS
Basic copper	0,017
Prepreg 7628(2)	0,346 +/-0,03
Basic copper	0,035
FR4 0,356	0,35 +/-0,04
Basic copper	0,035
Prepreg 2113(2)	0,176 +/-0,02
Basic copper	0,035
FR4 0,356	0,35 +/-0,04
Basic copper	0,035
Prepreg 2113(2)	0,176 +/-0,02
Basic copper	0,035
FR4 0,356	0,35 +/-0,04
Basic copper	0,035
Prepreg 7628(2)	0,346 +/-0,03
Basic copper	0,017

## 8 LAYERS 3,15 +/-0,3 LAB CODE: 173

MATERIAL	THICKNESS
Basic copper	0,017
Prepreg 7628(2)	0,346 +/-0,03
Basic copper	0,035
FR4 0,508	0,5 +/-0,05
Basic copper	0,035
Prepreg 7628(2)	0,346 +/-0,03
Basic copper	0,035
FR4 0,508	0,5 +/-0,05
Basic copper	0,035
Prepreg 7628(2)	0,346 +/-0,03
Basic copper	0,035
FR4 0,508	0,5 +/-0,05
Basic copper	0,035
Prepreg 7628(2)	0,346 +/-0,03
Basic copper	0,017